Io/Io^{LA}/Io^{LD} Firmware Update

Version 23.28 (Io), Version 4.8 (IoLA), and Version 3.5 (IoLD)

Firmware Update Contents

This software release provides updated firmware software for the Io Control Panel.

Changed In This Release

New firmware (model specific) that supports a new version of the Io Control Panel application.

To install the firmware

1. Ensure your Io/IoLA/IoLD is connected to the PowerMac and powered ON.
2. Download the firmware update from our webserver's Io support page (http://www.aja.com/support_Io.html). Ensure that you download the correct Firmware update for the type of Io you have (Io, IoLA, or IoLD).
3. The file downloaded is a ".zip" archive. Double-click it to expand the archive. The expanded file is a .dmg file. Double-click it.
4. After double-clicking, you will find a new volume mounted on your Mac desktop.
5. Inside the volume you will find the new Io Control Panel application and firmware updaters, one for each Io model.
6. Double-click the firmware updater file matching your Io model. The application will tell you the current Io version and serial number and ask you if you wish to procede. When run, the application will transfer the new firmware code to the Io/IoLA/IoLD.
7. Do not turn power OFF to the Io system while the application is updating the firmware. Follow the instructions provided by the application and wait until the update completes before disconnecting power from Io or powering it down.
8. After updating, ensure the Io/IoLA/IoLD works properly by capturing and then playing back some test source material.
9. You can run the new Io Control Panel application software once the firmware has been loaded into the Io.
10. If you have previously run any beta versions of the Io Control Panel software, you will have to go to the ***Presets*** tabbed window pane in the new version of the Control Panel, and then individually select each Preset from the pulldown menu and click the "Restore Factory Settings" button (for each). This is necessary because the format of the older presets is incompatible with the current control panel.