

FS-HDR v4.3.3 Firmware - Release Notes

Introduction

FS-HDR v4.3.3 firmware is a maintenance release that addresses an issue with the Motion Adaptive Deinterlacer control. This firmware update is highly recommended for all FS-HDR users.

Be sure to consult the Installation and Operation Guide (user manual) for detailed information about features and configuration guidelines. The most current documentation can always be found on FS-HDR's Support Page, <https://www.aja.com/products/fs-hdr#support>.

Fixes, Changes and Improvements in v4.3.3

- Fixes issue with Deinterlacer control that results in video artifacts. "Max" remains the default setting and the deinterlacer now performs as it did prior to this control being introduced. The "Off" setting has been removed.

Updating FS-HDR Firmware

Although the FS-HDR comes from the factory pre-installed with the latest firmware as of the time of manufacture, it may be necessary to re-flash the factory firmware or update to new firmware that has been posted on our AJA website. The following topics in these notes describe the steps required to upgrade the firmware in your FS-HDR.

Download the Latest Firmware

- Current and past releases of FS-HDR firmware are available on AJA's website.
 - To get the firmware, point your browser to: <https://www.aja.com/products/support/fs-hdr>.
- Once you see the update page, FS-HDR firmware files can be selected for downloading to your Mac or PC for upgrading your local machine.

Unpack the Firmware

The firmware update files are “ZIP” files, which you can open with a number of standard and third-party decompressor applications. The firmware image that you’ll install on the FS-HDR is a file with a name like FSHDR_ver_2.0.0.0.bin or similar. Depending on your Mac or Windows operating system settings, the “.bin” extension may not be visible to you in a file directory.

Uploading and Installing the Firmware to the FS-HDR

Uploading and installing the firmware update only requires a Mac or Windows computer that can “see” the FS-HDR via its Ethernet connection. Follow this procedure to install the firmware:

1. Point your browser at the FS-HDR's upgrade page by clicking on the “Firmware” menu link at the bottom of the navigation box on the left-hand side of any FS-HDR web page. The FS-HDR web pages are discussed in the FS-HDR User Manual.
2. Click the “Browse...” button to select the file you previously downloaded.
3. After you have selected a valid FS-HDR image file, click the “OK” button in the “Upload Firmware” prompt. The file you select will upload to the FS-HDR and be tested for validity. Incomplete, corrupted, or non-FS-HDR firmware files are rejected.
4. Click “Commit Uploaded Firmware” on the FS-HDR Update Firmware web page after the upload is finished.
5. Wait for the procedure to complete. When done, the FS-HDR Update Firmware web page will prompt you to restart your FS-HDR. Click the “Restart FS-HDR with New Firmware” button to begin the restart. Restart progress is shown on the front panel of the FS-HDR only. After the restart completes, the FS-HDR front panel “Status” menu is displayed, and the FS-HDR will be running the new firmware.
6. Once these steps are complete, the FS-HDR will be running the firmware you just uploaded until the next time you upgrade it. The configuration of the FS-HDR prior to the upgrade will be preserved. Ensure the new firmware is running by bringing up the FS-HDR web page again; the firmware version is displayed at the top of all FS-HDR web screens. If for some rare reason it didn’t update, you can then run through the update steps again.

Important Note: If there is a power outage or glitch during the firmware download, the FS-HDR will boot the older version and the upgrade process can then be re-started by the user. This happens because the FS-HDR has been designed with a safety feature where an internal “safe” copy of the previous firmware is retained in the event of any error in the updating.

Important Note: If upgrading from v2.5 (or older firmware) to v2.6 (or newer firmware), the ten USER LUT slots can be pre-loaded with a Unity LUT. This is a simple operation that can be performed in the FS-HDR web GUI. In the “User LUT” menu, select “Overwrite All” in the “Overwrite with Unity” parameter at the bottom of the page.

Important Note: If upgrading from v2.6 (or older firmware) to v3.0 (or newer firmware), the Colorfront Engine Color temp scale will change. The scale was 2000.0 to 11000.0 with a default of 4300.0. In v3.0, the scale is -10.000 to +10.000 with a default of 0.

Technical Support

AJA Technical Support is free and available to help you answer questions or resolve issues with any of your AJA products.

To contact AJA Technical Support:

Email: support@aja.com

Phone: +1-530-271-3190

Web: <https://www.aja.com/support/contact>

Shipping: 180 Litton Dr. Grass Valley, CA 95945 USA