

# AJA Desktop Software v17.1.3 Release Notes

## Rocky Linux v17.1.3 Drivers and Software for KONA

### Introduction

---

#### AJA Desktop Software

This unified software, driver and firmware package contains the necessities to use AJA video I/O hardware.

The following AJA applications are installed:

- AJA Control Panel v17.1.3:
  - For setup and control of your AJA KONA hardware, including firmware updates.
- AJA Control Room v17.1.3:
  - For high quality capture, monitoring, playback and output.
- AJA System Test v17.1.3:
  - For testing storage to determine if it will be possible to sustain frame and data rates for a chosen format(s).
- AJA NMOS v17.1.3:
  - Optional SMPTE ST 2110 application providing discovery, registration and control for AJA IP devices.

#### Operating System

- Note that, as of AJA Desktop Software release v17.0, Rocky Linux support replaces Red Hat/CentOS support.
- This driver/software version is compatible with Rocky Linux versions up to 8.10 and 9.5.
- Red Hat/CentOS 8 was EOL as of Dec 2021.
  - AJA SDK v16.2 was the final official SDK version supporting Red Hat/CentOS 8.
  - Note that after this release (17.1) applications may cease to work entirely with CentOS.
- Red Hat/CentOS 7 support, while expected to work, may have unknown issues.
- Note that some new features may not work with older distributions.
- Before running this installer, uninstall all previous versions of AJA software:
  - `sudo dnf remove ajantv2-dkms ajaretail`
- Two packages that must be installed: DKMS driver and AJA Retail Software.
  - The DKMS Driver installer requires the following package:
    - `sudo dnf install epel-release`
  - The driver installer must run either in a root shell or with root permissions.
    - `sudo dnf install ajantv2-dkms-XXXXXX.noarch.rpm`
    - Note: Use the exact package name here, see file name in install package
- The AJA Retail software must run either in a root shell or with root permissions.
  - `sudo dnf install ajaretail-ajaretail-XXXXXX.x86_64.rpm`
  - Note: Use the exact package name here, see file name in install package

- For GPU accelerated desktop display, an OpenCL version 1.2 or greater capable GPU is required.
- Check the Known Issues, Limitations and Additional Details section near the end of this document.
- Note that on later versions of GNOME, the extension management has been moved to its own dedicated app called GNOME Extensions (gnome-extensions-app). Execute the following to perform the installation:
  - Rocky 8:
    - `sudo dnf install gnome-shell-extension-appindicator gnome-tweaks`
    - open GNOME Tweaks
    - click Extensions on the left list
    - turn on KStatusNotifierItem/appindicator support
    - launch Control Panel
  - Rocky 9:
    - `sudo dnf install gnome-shell-extension-appindicator gnome-extensions-app`
    - log out of current user session (needed to do this for the Extensions app to see the newly installed extension)
    - log back in
    - open Extensions app
    - turn on AppIndicator and KStatusNotifierItem Support
    - launch Control Panel

### Third Party Software

AJA KONA hardware is used by many software and systems manufacturers, who provide their own software for user installation. The links below provide a guide to software support AJA is aware of, with additional software support being added frequently. Please contact the appropriate software vendor for information on whether AJA software or drivers are required when using their application. AJA recommends the latest released versions of 3rd party software for best performance:

<https://www.aja.com/compatibility/kona>

- Autodesk - Flame and related products
- AJA KONA hardware also comes with out-of-the-box support for OBS Studio as follows:
  - **OBS Project** - OBS Studio 30, 29.1.3, 28.1.x, 27.2.x (note that there are known issue with 29.13 and 30 for KONA X)

*In all cases, AJA recommends checking the system and OS requirements for 3rd party software packages with the software creator/vendor directly, to ensure a supportable configuration.*

## Relevant Products

The following products benefit from this update:

- KONA X
- KONA 5
- KONA 4
- KONA 1
- KONA HDMI
- KONA LHi
- KONA LHe Plus

## Recommendations in v17.1.3

---

- AJA offers a comprehensive SDK for developers who are interested in doing more with KONA, Corvid, and Io products. We have recently moved repositories to Github at <https://github.com/aja-video>. Our Github site now offers access to both open source and pre-compiled code and tools that make developing applications that support our products much easier.
- Note that AJA Desktop Software v17.x still works with EOL products, including Io XT, Io 4K, KONA IP, Io IP, T-TAP, and DNxIP. However, releases after v16.2 were no longer qualified with end-of-life products. What this means is that issues affecting these EOL products may arise that are not caught during the testing phase for new software releases, and these issues may not be fixed. In some cases, AJA may elect to fix issues that affect EOL products, but that cannot be guaranteed.
- Note that “End-of-Life” products will continue to receive best effort SDK support, but the supported SDK version may be frozen to the version available when the device went “End-of-Sale”.
- Note that Corvid HEVC (CORVID-HEVC-ATX6) is no longer being tested with new software releases.
- Note that some new PC motherboard and processor combinations do not offer full PCIe compatibility with add-on cards. Refer to our Hardware Compatibility Page on the AJA web site to see which systems have been tested in our lab and are known to work. <https://www.aja.com/page/system-configuration>

## Fixes and Improvements in v17.1.3

---

*Note: Items below are identified against the main AJA products affected.*

*These same issues may have also affected other AJA products that are not specifically called out.*

*Refer to the issue number shown below if contacting support for more information.*

### Fixes in this release:

- #863 – Fixed an issue where incoming SCTE104 packets would never be seen in the output signal for SD workflows using 525i or 625i.
- #960 – Fixed an issue that was causing the Linux NTV2 Acquire/Release functions to not properly detect a board that was in use by a different process, nor release boards that were owned by a dead process.

## Additional Details

---

### General

- “System Sleep” and “Hibernation” should not be used with KONA cards. All sleep and power efficiency modes should be disabled in the operating system settings.
- AJA Control Room captures can fall behind and may fail to retain the entirety of the recording when used with hard drives and SSDs that cannot maintain sufficient read/write speeds. Enabling deep buffers can improve the situation but may not prevent issues in all cases. Please use [AJA System Test](#) (free tool available on AJA web site) to measure disk performance to make sure your storage systems can handle the resolution and bit rates of the recordings you wish to make.
- Note that AJA Control Room cannot play clips in which “Time of Day” timecode was used, if the capture happened from one “Day” to the next “Day” across 12:00AM.
- Note that in some environments, PCIe Gen2 boards (KONA 4, KONA HDMI, KONA 1, Corvid 88, Corvid 44) do not link with 8 lanes after Windows boots. When using these boards on these systems, maximum performance or functionality may not be available. Please contact AJA support if you experience these issues. Affected motherboards and CPU’s:
  - Motherboards:
    - ASRock IMB-1314 with "PCIEX16\_1" and "PCIEX16\_2" slot (x8 supported slots)
    - AAEON MAX-Q670A with "PCIEX16\_1" and "PCIEX16\_2" slot (x8 supported slots)
      - (Note: The BIOS setting of CPU/PCIe slot for both motherboards do not affect the appearance ratio of the issue.)
  - CPUs when used on the motherboards above:
    - Core i7 13700
    - Core i7 12700
    - Core i9 12900

Note that additional information, as well as known issues, is located in the previous (v17.1) release notes at <https://www.aja.com/support>

## Technical Support

---

AJA Technical Support is free and available to help you answer questions or resolve issues with any of your AJA products.

### To contact AJA Technical Support:

Email: [support@aja.com](mailto:support@aja.com)

Phone: +1-530-271-3190

Fax: +1-530-274-9442

Web: <https://www.aja.com/support/contact>

Shipping: 180 Litton Dr. Grass Valley, CA 95945 USA