

# Release Notes – AJA Open I/O Plug-ins 10.3.2 for Windows



## General

---

This software release adds new features and improves functionality of the KONA LHe Plus, KONA LHi, KONA 3, KONA 3X, and KONA 3G cards, as well as the Io Express.

## Requirements and Recommendations

---

- Operating System Required: Windows 7 64-bit
- AJA Windows Driver 10.3.2 or later is required. The hardware drivers are not included in this installer package but can be downloaded from the AJA Support website.
- Before running this installer, uninstall all previous versions of AJA XENA or AJA Windows software and AJA Open I/O Plug-ins.
- Avid Media Composer 6.5, Symphony 6.5, or NewsCutter 10.5 required.
- QuickTime™ 7.6 or higher must be installed.
- For additional hardware recommendations and requirements, please see the links below:  
<http://www.aja.com/support/kona-pc/kona-pc-system-configuration.php>  
<http://www.aja.com/support/kona/kona-system-configuration.php>
- AJA recommends running this installer as an Administrator. To do this, right click on the installer and select 'Run As Administrator'. This 'Run As Administrator' option may not be present if Windows User Account Control (UAC) is turned off.

## Improvements

---

- Support for Avid Media Composer 6.5, Symphony 6.5 and NewsCutter 10.5
- Support for 'Audio Punch-In Tool' now added for using AJA device as the audio input device when doing voice overs. For the AJA device to be selectable in the Audio Punch-In Tool, it must first be selected in the Capture Tool:
  1. Open the Capture Tool
  2. Select the Video Input as AJA KONA or AJA Io
  3. Close the Capture Tool
  4. Open the Audio Punch-In Tool
  5. Select the Input Device as AJA KONA or AJA Io

# Known Issues and Limitations

---

- For the AJA device to be selectable in the Audio Punch-In Tool, it must first be selected in the Capture Tool:
  1. Open the Capture Tool
  2. Select the Video Input as AJA KONA or AJA Io
  3. Close the Capture Tool
  4. Open the Audio Punch-In Tool
  5. Select the Input Device as AJA KONA or AJA Io
- Indefinite looping of the timeline with Open I/O plug-in installed may cause Avid applications to stop playback and give an error message.
- When capturing Dual-Link RGB source using KONA 3 or KONA 3G, the E/E pass through signal may be incorrect on the Dual SDI output.
- The AJA hardware genlock may switch between 'Input' and 'Reference' when 'Reference' has been selected in the AJA Control Panel. Specifically, this is known to happen when attempting to batch capture in Media Composer, causing some clips in the batch to not be captured. To work around this issue, select 'Input' genlock in the AJA Control Panel when batch capturing.
- Occasionally analog video input will not be detected correctly in the Media Composer Capture Tool. As a workaround, play the source video when you start up Media Composer.